





# Trulink® UXGA Monitor Splitter/Extender with 3.5mm Audio

- Broadcast your computer's audio and video outputs to two monitors
- Daisy-chain splitters to expand the number of monitors and speakers
- Built-in video signal enhancement allows monitors to be placed up to 210 feet away
- Use the 3.5mm audio outputs to drive either speakers or earphones
- 1-year warranty

## Specifications: Trulink® UXGA Monitor Splitter/Extender with 3.5mm Audio

### **Signal Specifications:**

Video Signal Supported: XGA, SVGA, VGA, and MultiSync®

Maximum Resolution Supported:  $2048 \times 1536$  at 60Hz

Video Signal Bandwidth: 400MHz Audio Operation Frequency: 50Hz ~ 15kHz

Audio Input Impedance: 20kΩ

#### **Power Adapter Specifications:**

120V AC 60Hz, 0.2A Power Input: Power Output: 12V DC, 600mA

Power Cable Length: 6ft DC Power Pin Diameter: 5.5mm Center Pin Polarity: **Positive** 

### **Physical Characteristics:**

Output Connectors (39967):

Output Connectors (39968):

LED Lights: Power - Green x 1 HD15 (VGA) Female x 1 Input Connectors:

3.5mm Female x 1 HD15 (VGA) Female x2 3.5mm Female x 2 HD15 (VGA) Female x 4

3.5mm (VGA) Female x 4 **Enclosure Material:** 

Metal

39967 - 20 x 85 x 180mm Dimensions: 39968 - 40 x 70 x 196mm

Part Number	Description	Weight (lbs)
39967	2-Port Trulink® UXGA Monitor Splitter/Extender with 3.5mm Audio	2.06
39968	4-Port Trulink® UXGA Monitor Splitter/Extender with 3.5mm Audio	2.37